



Thank you for buying a StreetWorks product. Be confident that it will provide the quality and performance that you demand for your car.
Please read and understand all installation instructions before beginning. Planning and preparation will make the entire process easy and quick.

Most aftermarket power window motors are 2-wire polarity reversing which means that for the window to go up there needs to be a positive and a negative provided to the motor lead wires at the same time. (For example let's say the motor lead wires are White and Brown, when you press the up button white sees a positive and brown sees a negative for the window to go up. When the down button is pressed the polarity needs switch so the white sees negative and brown sees a positive for the window to go down) If you have more than (2) wires or the case of the motor calls to be grounded this module will not work.

There are other ways to trigger this module along with the interior switch. If you have a remote control or an outside momentary switch with a positive output you can trigger the module on the YELLOW wire. Determine which direction you would like the window to go with your external switch and connect it to the proper YELLOW trigger wire.

Polarity Reversing Module #L07W-25

This Module is designed to reverse the polarity for the motors of power windows, power door locks, or actuators allowing the use of a "3-wire" switch, remote control or any (2) positive triggers.

- Small and compacted
- 25 amps max

